



AiT Semiconductor Inc.

www.ait-ic.com

AM50N10

MOSFET

100V, 50A N-CHANNEL MOSFET

DESCRIPTION

The AM50N10 is available in TO-252 package.

BVDSS	RDS(ON)	ID
100V	17mΩ	50A
	21.5 mΩ	

FEATURE

- $R_{DS(ON)}^{typ.} = 17 \text{ m}\Omega @ V_{GS}=10\text{V}$
- $R_{DS(ON)}^{typ.} = 21.5 \text{ m}\Omega @ V_{GS}=4.5\text{V}$
- Low $R_{DS(on)}$ & FOM
- Extremely Low Switching Loss
- Excellent Stability and Uniformity
- Fast Switching and Soft Recovery


APPLICATION

- Power switching application
- Hard switched and high frequency circuits
- Uninterruptible power supply

ORDERING INFORMATION

Package Type	Part Number	
TO-252 SPQ:2,500pcs/Reel	D	AM50N10DR
		AM50N10DVR
Note	V: Halogen free Package R: Tape & Reel	
AiT provides all RoHS products		

PIN DESCRIPTION



TO-252

Pin#	Symbol	Function
1	G	Gate
2,4	D	Drain
3	S	Source



AiT Semiconductor Inc.

www.ait-ic.com

AM50N10

MOSFET

100V, 50A N-CHANNEL MOSFET

ABSOLUTE MAXIMUM RATINGS

$T_A = 25^\circ\text{C}$, unless otherwise specified.

V_{DS} , Drain-Source Voltage		100V
V_{GS} , Gate-Source Voltage		$\pm 20\text{V}$
I_D , Drain Current	$T_c=25^\circ\text{C}$	50A
	$T_c=100^\circ\text{C}$	28.5A
I_{DM} , Pulsed Drain Current ⁽¹⁾		180A
E_{AS} , Avalanche Energy ⁽²⁾		81mJ
P_D , Total Power Dissipation ⁽³⁾	$T_c=25^\circ\text{C}$	72W
	$T_c=100^\circ\text{C}$	28.8W
T_J , Junction Temperature Range		-55°C~+150°C
T_{STG} , Storage Temperature Range		-55°C~+150°C

Stresses above may cause permanent damage to the device. These are stress ratings only and functional operation of the device at these or any other conditions beyond those indicated in the Electrical Characteristics are not implied. Exposure to absolute maximum rating conditions for extended periods may affect device reliability.

(1) Repetitive rating; pulse width limited by max. junction temperature.

(2) $V_{DD}=50\text{V}$, $V_{GS}=10\text{V}$, $L=5\text{mH}$, $I_{AS}=5.7\text{A}$.

(3) P_d is based on max. junction temperature, using junction-case thermal resistance.

THERMAL RESISTANCE

Parameter		Min.	Typ.	Max.	Unit
$R_{\theta JA}$, Thermal Resistance Junction-to-Ambient*	$t \leq 10\text{s}$	-	15	20	°C/W
$R_{\theta JA}$, Thermal Resistance Junction-to-Ambient*	Steady-State	-	40	50	
$R_{\theta JC}$, Thermal Resistance Junction-to-Case	Steady-State	-	1.35	1.7	

*The value of $R_{\theta JA}$ is measured with the device mounted on 1in2 FR-4 board with 2oz. Copper, in a still air environment with $T_A = 25^\circ\text{C}$. The Power dissipation P_{DSM} is based on $R_{\theta JA} \leq 10\text{s}$ and the maximum allowed junction temperature of 150°C . The value in any given application depends on the user's specific board design.



ELECTRICAL CHARACTERISTICS

T_J = 25°C, unless otherwise specified.

Parameter	Symbol	Conditions	Min.	Typ.	Max.	Unit
Static Parameter						
Drain-Source Breakdown Voltage	BV _{DSS}	V _{GS} = 0V, I _D =250µA	100	-	-	V
Zero Gate Voltage Drain Current	I _{DSS}	V _{DS} =100, V _{GS} =0V	-	-	1	µA
Gate-Body Leakage Current	I _{GSS}	V _{GS} = ±20V, V _{DS} =0V	-	-	±100	nA
Gate Threshold Voltage	V _{GS(TH)}	V _{DS} = V _{GS} , I _D =250µA	1	1.8	3	V
Static Drain-Source On-Resistance	R _{DS(ON)}	V _{GS} = 10V, I _D =20A	-	14	17	mΩ
		V _{GS} = 4.5V, I _D =20A	-	17	21.5	mΩ
Diode Forward Voltage	V _{SD}	I _S =20A, V _{GS} =0V	-	-	1.3	V
Maximum Body-Diode Continuous Current	I _S		-	-	45	A
Gate Resistance	R _G	f= 1 MHz, Open drain	-	1	-	Ω
Dynamic Characteristics						
Input Capacitance	C _{iss}	V _{GS} =0V, V _{DS} =50V, f=1MHz	-	1135	-	pF
Output Capacitance	C _{oss}		-	399	-	
Reverse Transfer Capacitance	C _{rss}		-	18	-	
Switching Characteristics						
Total Gate Charge	Q _g	V _{GS} =10V, V _{DS} =50V, I _D =25A	-	16	-	nC
Gate-Source Charge	Q _{gs}		-	5.6	-	
Gate-Drain Charge	Q _{gd}		-	2.4	-	
Reverse Recovery Charge	Q _{rr}	I _F =20A, di/dt=100A/us	-	42	-	ns
Reverse Recovery Time	t _{rr}		-	39.8	-	
Turn-on Delay Time	t _d (ON)	V _{GS} =10V, V _{DD} =50V, I _D =25A R _{GEN} =2.2Ω	-	39.2	-	
Turn-on Rise Time	t _r		-	11	-	
Turn-off Delay Time	t _d (OFF)		-	53.2	-	
Turn-off fall Time	t _f		-	15.8	-	

**TYPICAL PERFORMANCE CHARACTERISTICS**

Fig1. Output Characteristics




Fig 2. Transfer Characteristics




Fig 3. Capacitance Characteristics




Fig 4. Gate Charge




Fig 5. On-Resistance
vs. Drain Current and Gate Voltage

Fig 6. Normalized On-Resistance





AiT Semiconductor Inc.

www.ait-ic.com

AM50N10

MOSFET

100V, 50A N-CHANNEL MOSFET

Fig7. Drain Current




Fig 8. Safe Operation Area





Fig 9. Normalized Maximum Transient Thermal Impedance





AiT Semiconductor Inc.

www.ait-ic.com


AM50N10

MOSFET


100V, 50A N-CHANNEL MOSFET

PACKAGE INFORMATION


Dimension in TO-252 (Unit: mm)




TOP VIEW



SIDE VIEW



BOTTOM VIEW



SUGGESTED SOLDER PAD LAYOUT

Symbol	MILLIMETERS	
	Min.	Max.
A1	0.000	0.200
A2	2.200	2.400
A3	0.900	1.100
b	0.660	0.860
c	0.460	0.580
D	6.500	6.700
D1	5.150	5.450
D2	4.600	4.950
E	9.900	10.300
E1	6.000	6.200
E2	5.150	5.450
e	2.286 BSC	
L	1.250	1.750
L1	0.900	1.270
L2	1.400	1.900
L3	0.600	1.000
L4	2.900 REF	
θ	0°	10°



AiT Semiconductor Inc.

www.ait-ic.com

AM50N10

MOSFET

100V, 50A N-CHANNEL MOSFET

IMPORTANT NOTICE

AiT Semiconductor Inc. (AiT) reserves the right to make changes to any its product, specifications, to discontinue any integrated circuit product or service without notice, and advises its customers to obtain the latest version of relevant information to verify, before placing orders, that the information being relied on is current.

AiT Semiconductor Inc. integrated circuit products are not designed, intended, authorized, or warranted to be suitable for use in life support applications, devices or systems or other critical applications. Use of AiT products in such applications is understood to be fully at the risk of the customer. As used herein may involve potential risks of death, personal injury, or server property, or environmental damage. In order to minimize risks associated with the customer's applications, the customer should provide adequate design and operating safeguards.

AiT Semiconductor Inc. assumes to no liability to customer product design or application support. AiT warrants the performance of its products of the specifications applicable at the time of sale.