



AiT Semiconductor Inc.

www.ait-ic.com

AM15N10

MOSFET

100V, 15A N-CHANNELPOWER MOSFETS

DESCRIPTION

The AM15N10 is available in PDFN8(3x3) Package.

BVDSS	RDS(on)	ID
100V	85mΩ	15A


FEATURE

- Low Gate Charge
- Low Ciss
- Fast Switching
- Improved dv/dt Capability

APPLICATION

- High Frequency Switching and Synchronous Rectification.
- DC/DC Converter.

PIN DESCRIPTION



PDFN8 (3x3)

Pin#	Symbol	Function
1, 2, 3	S	Source
4	G	Gate
5, 6, 7, 8	D	Drain

ABSOLUTE MAXIMUM RATINGS

T_C=25°C,unless otherwise noted.

V _{DSS} , Drain-Source Voltage	100V
V _{GS} , Gate-Source Voltage	±20V
I _D , Continuous Drain Current	15A
	9A
I _{DM} , Pulsed Drain Current *	60A
E _{AS} , Single Pulse Avalanche Energy	29mJ
P _D , Maximum Power Dissipation	20.8W
T _{STG} , Storage Temperature Range	-50°C ~ +150°C
T _J , Operating Junction Temperature Range	-50°C ~ +150°C
TL, Maximum Lead Temperature for Soldering Purposes, 1/8" from Case for 5 Seconds	260°C
R _{th(ch-c)} , Thermal Resistance, Channel to Case	6°C/W

Stresses above may cause permanent damage to the device. These are stress ratings only and functional operation of the device at these or any other conditions beyond those indicated in the Electrical Characteristics are not implied. Exposure to absolute maximum rating conditions for extended periods may affect device reliability.

* Repetitive Rating: pulse width limited by maximum junction temperature.



ELECTRICAL CHARACTERISTICS

T_C=25°C,unless otherwise noted.

Parameter	Symbol	Conditions	Min	Typ.	Max	Unit
Static Characteristic						
Drain-Source Breakdown Voltage	BV _{DSS}	V _{GS} =0V, I _D =250μA	100	-	-	V
Zero Gate Voltage Drain Current	I _{DSS}	V _{DS} = 100V, V _{GS} =0V	-	-	1	μA
Gate-Source Leakage Current, Forward	I _{GSSF}	V _{DS} = 0V, V _{GS} =20V	-	-	100	nA
Gate-Source Leakage Current, Reverse	I _{GSSR}	V _{DS} = 0V, V _{GS} = -20V	-	-	-100	nA
Drain-Source On-State Resistance	R _{D(S)ON}	V _{GS} =10V, I _D =5A	-	71	85	mΩ
		V _{GS} =4.5V, I _D =3A	-	82	110	
Gate Threshold Voltage	V _{GS(th)}	V _{DS} =V _{GS} , I _D =250μA	1.2	-	2.5	V
Gate Resistance	R _g	V _{GS} =0V, V _{DS} Open, f=1MH	-	0.8	-	Ω
Forward Transconductance	g _{fs}	V _{DS} =5V, I _D =5A	-	3.6	-	S
Dynamic Characteristic						
Input Capacitance	C _{iss}	V _{DS} =25V, V _{GS} =0V, f=1MHz	-	1188	-	pF
Output Capacitance	C _{oss}		-	55	-	
Reverse Transfer Capacitance	C _{rss}		-	44	-	
Turn-On Delay Time	t _{d(on)}	V _{DD} = 50V, R _L =14Ω V _{GS} = 10V	-	13.4	-	ns
Turn-On Rise Time	t _r		-	0.8	-	
Turn-Off Delay Time	t _{d(off)}		-	36.4	-	
Turn-Off Fall Time	t _f		-	4.6	-	
Gate Charge Characteristic						
Total Gate Charge	Q _G	V _{DS} = 80V, I _D =15A, V _{GS} = 10V	-	23	-	nC
Gate-Source charge	Q _{gs}		-	5.5	-	
Gate-Drain charge	Q _{gd}		-	5.5	-	
Reverse Diode						
Continuous Diode Forward Current	I _s		-	-	15	A
Pulsed Current Forward Current	I _{s,pulse}		-	-	60	A
Diode Forward Voltage	V _{SD}	V _{GS} =0V, I _s =5A	-	-	1.20	V
Reverse Recovery Time	t _{rr}	I _F =1A, V _D =30V, di/dt=100A/μs	-	27	-	ns
Reverse Recovery Charge	Q _{rr}		-	19.8	-	nC



AiT Semiconductor Inc.

www.ait-ic.com

AM15N10

MOSFET

100V, 15A N-CHANNELPOWER MOSFETS

TYPICAL PERFORMANCE CHARACTERISTICS

Fig 1. Typical Output Characteristics




Fig 3. Typical Body Diode Transfer Characteristics




Fig 5. Typical Breakdown Voltage vs. Junction Temperature




Fig 2. Typical Gate Charge vs. Gate to Source Voltage




Fig 4. Typical Capacitance vs. Drain to Source Voltage





Fig 6. Typical Drain to Source on Resistance vs. Junction Temperature





AiT Semiconductor Inc.

www.ait-ic.com

AM15N10

MOSFET

100V, 15A N-CHANNELPOWER MOSFETS

Fig 7. Maximum Forward Bias Safe Operating Area




Fig 8. Typical Drain to Source ON Resistance vs. Drain Current




Fig 9. Maximum EAS vs. Channel Temperature




Fig 11. Typical Transfer Characteristics




Fig 10. Typical Threshold Voltage vs. Case Temperature




Fig 12. Maximum Power Dissipation vs. Case Temperature






Fig 13. Maximum Effective Thermal Impedance, Junction to Case




Fig 14. Peak Diode Recovery dv/dt Test Circuit





Fig 15. Peak Diode Recovery dv/dt Waveforms





AiT Semiconductor Inc.

www.ait-ic.com

AM15N10

MOSFET

100V, 15A N-CHANNELPOWER MOSFETS

Fig 16. Switching Test Circuit




Fig 17. Switching Waveforms




Fig 18. Gate Charge Test Circuit




Fig 19. Gate Charge Waveform




Fig 20. Unclamped Inductive Switching Test Circuit







Fig 21. Unclamped Inductive Switching Waveforms






PACKAGE INFORMATION

Dimension in PDFN8(3x3) (Unit: mm)



RECOMMENDED LAND PATTERN



Symbol	Millimeters (mm)	
	Min.	Max.
A	0.700	1.000
b	0.240	0.400
c	0.100	0.250
D	3.000	3.250
D1	3.100	3.500
D2	0.300	0.500
D3	2.500	2.700
D4	2.350	2.550
E	2.900	3.100
E1	3.150	3.450
E2	1.650	1.850
E3	0.480	0.680
E4	0.230	0.500
E5	0.200	0.400
E6	0.075	0.250
e	0.550	0.750
K	0.520	0.820
L	0.250	0.550
L1	0.000	0.100
L2	0.280	0.580
L3	0.880	1.080



AiT Semiconductor Inc.

www.ait-ic.com

AM15N10

MOSFET

100V, 15A N-CHANNELPOWER MOSFETS

IMPORTANT NOTICE

AiT Semiconductor Inc. (AiT) reserves the right to make changes to any its product, specifications, to discontinue any integrated circuit product or service without notice, and advises its customers to obtain the latest version of relevant information to verify, before placing orders, that the information being relied on is current.

AiT Semiconductor Inc. integrated circuit products are not designed, intended, authorized, or warranted to be suitable for use in life support applications, devices or systems or other critical applications. Use of AiT products in such applications is understood to be fully at the risk of the customer. As used herein may involve potential risks of death, personal injury, or server property, or environmental damage. In order to minimize risks associated with the customer's applications, the customer should provide adequate design and operating safeguards.

AiT Semiconductor Inc. assumes no liability to customer product design or application support. AiT warrants the performance of its products of the specifications applicable at the time of sale.